

GENERATOR

SDG150S-3B1

BRAND	AIRMAN
MODEL	SDG150S-3B1
GENERATOR	
Type	Dual Voltage
Frequency (Hz)	50 / 60
3-phase 4 wires	
- Prime Output (kVA)	125 / 150
- Stanby Output (kVA)	137.5 / 165
- Voltage (V)	200/400 / 220/440
- Current (A)	361/180 / 394/197
Single-phase auxiliary output	
- Voltage (V)	100 / 110
- Dedicated terminals (kVA)	10×2 / 11×2
- Outlets (kVA)	1.5×2 / 1.65×2
Power factor (%)	3-phase 80 (lagging) / Single-phase 100

ENGINE	
Make, Model	ISUZU BH-6HK1X
Type	Direct-Injection, Turbo-Charged, Intercooled
Rated output (kW)	119 / 142
Rated output (PS)	162 / 193
Rated speed (min-1)	1,500 / 1,800
Fuel tank capacity (L)	250
Engine oil amount (L)	38.0
Battery × quantity	95D31R×2
DIMENSION & WEIGHT, etc	
L×W×H (mm)	3,190×1,180×1,470
Dry weight (kg)	2,050
Operating weight (kg)	2,480
Sound power level in decibels (dB)	93 / 95
Sound pressure level (dB[A])	64 / 68
Designated emissions regulation	JPN Stage 3

